

## Flash update RFX software

Binary software files are available for:

RFX-433      USB or WiFi

RFX-433EMC USB or WiFi or MQTT

RFX-868      USB or WiFi or MQTT

All versions support P1.

## Flash RFX MQTT software

Binary MQTT software files are available for:

RFX-433EMC and RFX-868

All versions support P1.

**Important:** select all files and from the same directory.

You can use a web tool to flash the RFX connected to USB and use these parameters:

**0x0 = RFXS3.ino.bootloader.bin**

**0x8000 = RFXS3.ino.partitions.bin**

**0xE000 = boot\_app0.bin**

**0x10000 = RFXS3.ino.bin**

Use for example the solution as described here:

<https://blog.spacehuhn.com/espwebtool>

<https://esp.huhn.me/>

- Click Connect and select the correct USB COM port
- Select files (**note: enter 0 at ...ino.bootloader.bin**)  
**Important:** select all files from the same directory!!
- Click Program

If the connection reports a problem with the Program command:

Keep the RESET button pressed, click PROGRAM, release the RESET button.

version 4015/8002 and up

0x 0	RFXS3.ino.bootloader.bin
0x 8000	RFXS3.ino.partitions.bin
0x E000	boot_app0.bin
0x 10000	RFXS3.ino.bin

RESET 

ERASE

PROGRAM